

EECS20n, Quiz 5, 12/3/01

The quiz will take 15 minutes. Write your response on the sheet. Use the back if you need more space.

Please print your name here:

Last Name _____ First _____ Lab _____

Consider a continuous-time system with input signal x and output signal y where

$$\forall t \in \text{Reals}, \quad y(t) = x(t)e^{i\omega_1 t}$$

where $\omega_1 > 0$ is a real number.

1. Give the Fourier transform Y of y in terms of the Fourier transform X of x .
2. Is the system linear?
3. Is the system time invariant?

For reference, the continuous-time Fourier transform relation is

$$X(\omega) = \int_{-\infty}^{\infty} x(t)e^{-i\omega t} dt.$$

The inverse relation is

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(\omega)e^{i\omega t} d\omega.$$