

Figure 1: Given x , sketch y .

EECS20N, Quiz 2, 9/27/99

The quiz will count as one homework. It will take 15 minutes. Do your calculations on the sheet and put a box around your answer.

Please print your name here:

Last Name _____ First _____

1. The signal $x : \mathbb{R} \rightarrow \mathbb{R}$ is sketched in Figure 1.

(a) In the space provided carefully sketch the signal y , where

$$\forall t, \quad y(t) = \sum_{k=-\infty}^{\infty} x(t - 2k).$$

(b) Suppose t is in seconds. The period of y is _____

2. The periodic signal $x : \mathbb{R} \rightarrow \mathbb{R}$ is given by

$$\forall t, \quad x(t) = 2 \sin(2\pi 60t + \pi/4) + 0.5 \sin(2\pi 120t + \pi/8).$$

(a) The period of x in seconds is _____

(b) Suppose x is input to a LTI system whose frequency response is

$$H(\omega) = \begin{cases} 1, & \text{if } |\omega| \leq 2\pi 80 \text{ rad/sec} \\ 0, & \text{otherwise} \end{cases}$$

Let y be the output signal. Then

$$\forall t, \quad y(t) = \text{_____}$$